INFORMATION TO USERS

This material was produced from a microfilm copy of the original document. While the most advanced technological means to photograph and reproduce this document have been used, the quality is heavily dependent upon the quality of the original submitted.

The following explanation of techniques is provided to help you understand markings or patterns which may appear on this reproduction.

- 1. The sign or "target" for pages apparently lacking from the document photographed is "Missing Page(s)". If it was possible to obtain the missing page(s) or section, they are spliced into the film along with adjacent pages. This may have necessitated cutting thru an image and duplicating adjacent pages to insure you complete continuity.**
- 2. When an image on the film is obliterated with a large round black mark, it is an indication that the photographer suspected that the copy may have moved during exposure and thus cause a blurred image. You will find a good image of the page in the adjacent frame.**
- 3. When a map, drawing or chart, etc., was part of the material being photographed the photographer followed a definite method in "sectioning" the material. It is customary to begin photoing at the upper left hand corner of a large sheet and to continue photoing from left to right in equal sections with a small overlap. If necessary, sectioning is continued again — beginning below the first row and continuing on until complete.**
- 4. The majority of users indicate that the textual content is of greatest value, however, a somewhat higher quality reproduction could be made from "photographs" if essential to the understanding of the dissertation. Silver prints of "photographs" may be ordered at additional charge by writing the Order Department, giving the catalog number, title, author and specific pages you wish reproduced.**
- 5. PLEASE NOTE: Some pages may have indistinct print. Filmed as received.**

University Microfilms International

300 North Zeeb Road
Ann Arbor, Michigan 48106 USA
St. John's Road, Tyler's Green
High Wycombe, Bucks, England HP10 8HR

77-29,344

SWEATT, William Charles, 1944-
DESIGNING HOLOGRAPHIC OPTICAL
ELEMENTS.

The University of Arizona, Ph.D., 1977
Physics, optics

Xerox University Microfilms, Ann Arbor, Michigan 48106

© 1977

WILLIAM CHARLES SWEATT

ALL RIGHTS RESERVED

DESIGNING HOLOGRAPHIC OPTICAL ELEMENTS

by

William Charles Sweatt

A Dissertation Submitted to the Faculty of the

COMMITTEE ON OPTICAL SCIENCES (GRADUATE)

In Partial Fulfillment of the Requirements
For the Degree of

DOCTOR OF PHILOSOPHY

In the Graduate College

THE UNIVERSITY OF ARIZONA

1 9 7 7

Copyright 1977 William Charles Sweatt

THE UNIVERSITY OF ARIZONA

GRADUATE COLLEGE

I hereby recommend that this dissertation prepared under my
direction by William Charles Sweatt
entitled Designing Holographic Optical Elements
_____ be accepted as fulfilling the dissertation requirement for the
degree of Doctor of Philosophy _____

Robert D. Thomson
Dissertation Director

19 Aug 77
Date

As members of the Final Examination Committee, we certify
that we have read this dissertation and agree that it may be
presented for final defense.

H. N. Barrett
James C. Wyant

Aug. 1, 1977
Aug. 2, 1977

Final approval and acceptance of this dissertation is contingent
on the candidate's adequate performance and defense thereof at the
final oral examination.

STATEMENT BY AUTHOR

This dissertation has been submitted in partial fulfillment of requirements for an advanced degree at The University of Arizona and is deposited in the University Library to be made available to borrowers under rules of the Library.

Brief quotations from this dissertation are allowable without special permission, provided that accurate acknowledgment of source is made. Requests for permission for extended quotation from or reproduction of this manuscript in whole or in part may be granted by the copyright holder.

SIGNED: WC Smith

ACKNOWLEDGMENTS

I would like to thank my wife, Louise, for not offering to help as I frantically searched for errant minus signs. I appreciate the towels she handed me during those ordeals. Her presence was a great comfort.

I also wish to thank my dissertation directors, Jim Wyant and Bob Shannon. They each contributed a few pieces to the puzzle as well as a lab to work in, computer funds, and, most important, good advice. I have truly enjoyed working with them.

Don McCauley of NWC, China Lake, California, convinced the Navy to fund most of this effort and led me through the dichromated gelatin jungle. Thanks, Don.

Several authors contributed experimental techniques, sympathy, and/or philosophy; including Professors Barrett and Shack, George Hopkins, Rich Shagam, etc.

TABLE OF CONTENTS

	Page
LIST OF ILLUSTRATIONS	vi
LIST OF TABLES	viii
ABSTRACT	ix
 CHAPTER	
I. INTRODUCTION	1
The Lens Analog	3
Thick HOE's	4
II. THE LENS ANALOGY	7
Technique	8
Planar Holographic Optical Elements	10
Hologram on a Spherical Surface	18
Equivalent Lens Surfaces Resulting from Spherically Aberrated Waves	20
Conclusions	23
III. DESIGNING THICK TRANSMITTING HOLOGRAPHIC OPTICAL ELEMENTS	25
Derivation	26
Experimental Verification	33
Conclusions	37
IV. DESIGNING THICK REFLECTING HOLOGRAPHIC OPTICAL ELEMENTS	40
Construction Parameters	44
Experimental Verification	45
Conclusions	47
V. CONSTRUCTING THICK HOLOGRAPHIC OPTICAL ELEMENTS	51
Details About the Emulsion and Substrate, Thickness of the Substrate	51
Index of the Emulsion	55

TABLE OF CONTENTS--Continued

	Page
Thickness of the Emulsion	58
Optical Systems to Construct HOE's	60
Conclusions	73
VI. CONCLUSIONS	74
APPENDIX A. FIRST AND THIRD ORDER PROPERTIES OF HOLOGRAPHIC OPTICAL ELEMENTS . . .	76
APPENDIX B. THIRD-ORDER ABERRATIONS OF A THICK TRANSMITTING HOE	86
APPENDIX C. CONSTRUCTING A THICK REFLECTING HOE . .	89
APPENDIX D. ACHROMATIC TRIPLET USING HOLOGRAPHIC OPTICAL ELEMENTS	92
REFERENCES	99

LIST OF ILLUSTRATIONS

Figure	Page
1.1 Systems that will construct (a) thick reflecting HOE's and (b) transmitting HOE's	2
2.1 Hologram exposing geometry	11
2.2 Lens equivalent of holographic optical element	13
2.3 Exploded view of lens equivalent	14
2.4 Geometry of holographic imaging system; hologram in x-y plane	16
2.5 Hologram on spherical surface (exposing geometry)	19
2.6 Aberrated wavefront (dotted line) and reference sphere (solid line)	21
3.1 Desired wavefront geometry	28
3.2 Ray passing through a thick emulsion	29
3.3 Reconstruction geometry: $\lambda_r = 632.8\text{nm}$	35
3.4 Constructing geometry	36
3.5 Point spread function of (a) corrected HOE at 632.8nm and (b) uncorrected HOE exposed with point sources	38
4.1 HOE construction geometry showing the spherical aberration W_c and W'_c and the resulting wavefront tilt γ'_c and γ_c	41
4.2 Constructing beams interfering in the emulsion	43
4.3 Maximum construction wavelength vs. image magnification	46

LIST OF ILLUSTRATIONS--Continued

Figure		Page
4.4	Optical system to construct 205mm f.l reflecting HOE	48
4.5	Point spread function of HOE at 514.5nm . . .	49
5.1	Thickness variation of substrate	53
5.2	Abb� refractometer showing interference between the two reflections	56
5.3	Index matching (a) trench cut in emulsion; (b) Mach-Zehnder interferometer (BS = beam splitter, LG = liquid gate, I = image); (c) example image showing OPD = $\pm D/4$	59
5.4	Systems producing third order spherical aberration	61
5.5	Sign convention for aberration generation scheme	65
5.6	Functions $f(x)$ [Eq. (5.4)] and $g(x)$ for $n = 1.52$	67
5.7	Flow charts	68
5.8	Constructing a reflecting HOE	71

LIST OF TABLES

Table		Page
2.1	Ray tracing comparison of lens analogy with HOE	17

ABSTRACT

New methods of designing and constructing holographic optical elements (HOE) are presented. An exact lens analog allows HOE's to be designed as lenses using standard lens design codes. The lens analog has a huge index of refraction and very small curvatures. Thick reflecting and transmitting HOE's will have better image quality and efficiency if they are constructed with spherically aberrated wavefronts. The reconstruction wavelength is allowed to differ from the construction wavelength. The index of refraction and thickness of the emulsion may also change.

CHAPTER I

INTRODUCTION

In this work, new techniques are developed for designing and constructing holographic optical elements (abbreviated HOE throughout this dissertation). The most interesting discovery is an exact lens analog for a HOE. Using this analogy, optical systems containing HOE's can be analyzed or optimized using unmodified standard lens design programs. In thick HOE's constructed with spherical wavefronts, the efficiency and image quality are coupled and one will suffer if the other is optimized. It is shown here that if thick HOE's are constructed with correctly aberrated wavefronts, the efficiency and image quality can both be optimized. A complete design scheme is presented.

HOE's are commonly constructed using two interfering spherical beams of monochromatic light. Figure 1.1 shows the simplest optical systems that will construct HOE's. Figure 1.1a will generate a thick reflecting HOE. The system shown in Fig. 1.1b will construct a thick transmitting HOE or any thin HOE. Classically, the design of such elements has been done using the first order properties and third order aberrations developed by

Fig. 1.1. Systems that will construct (a) thick reflecting HOE's and (b) transmitting HOE's.

Champagne (1967), Meier (1965), and Latta (1971). Real rays can be easily traced using the equations of Offner (1966). The efficiency of a thick HOE is normally determined using Kogelnik's (1969) theory. A computerized optimization scheme has been developed by Latta and Fairchild (1973). Logically enough, all of these schemes are based on diffraction theory.

The Lens Analog

The light focusing properties of a HOE and a thin lens are very similar. In fact, as the index of refraction of the lens is increased and the curvatures are correspondingly decreased, the analogy improves. As the index of refraction reaches 100 or more, and a few further refinements are added, we find that we have a nearly exact analogy. As stated above, this equivalent lens is useful because it allows us to design HOE's with a standard lens design computer program. Also, we can optimize a mixed system containing HOE's and common elements like lenses and mirrors as a unit rather than in two parts as is usually done.

This scheme is described in detail in Chapter II. It is shown that as the index of refraction becomes large, the thickness of the equivalent lens becomes negligible and the model works well for off-axis rays. The dispersion (inverse of the Abbé number) is derived. Then

the hyperbolic shapes for the lens surfaces are derived using lens theory. To prove that the model works, some real rays are traced through a HOE and then through a HOE-equivalent lens. The lens results converge beautifully as the index of refraction is increased.

Holographic optical elements can also be made on curved surfaces. An exact lens analog for a HOE on a spherical substrate is derived. In preparation for Chapters III and IV, the lens analog for a HOE constructed with spherically aberrated waves is also presented.

Thick HOE's

We present a scheme for designing thick transmission and reflection HOE's with improved image quality. If we introduce the correct amount of third order spherical aberration into both of the interfering wavefronts, we can construct a HOE with the required power, the proper amount of spherical aberration, and Bragg efficiency optimized to third order.

In Chapters III and IV the constructing geometries for thick reflecting and transmitting holographic elements are developed. This includes the paraxial foci of the two constructing beams and the amount of third order spherical aberration in each beam. In Chapter III, the paraxial foci for a transmitting thick HOE are derived to give the correct power and optimize the Bragg efficiency in the paraxial

region. The amount of third order spherical aberration needed in each beam is derived in Appendix B.

The construction parameters for a thick reflecting HOE are derived in Appendix C and discussed in Chapter IV. Two special conditions are mentioned that do not limit the design procedure, but may complicate it. Experimental verification is presented in both Chapters III and IV. Chapter V discusses engineering details required to put this theory to work. Before thick HOE's can be designed, the film's properties must be known. Methods are described for determining the variation of the thickness of a flat substrate and the index of refraction and thickness of the emulsion.

Optical systems that will produce the aberrated wavefronts are discussed in the second half of Chapter V. A third order design scheme using plano-convex and plano-concave lenses is presented. Further optimization of the aberrated wavefronts is also discussed.

Third order aberrations for a general HOE on a flat substrate are presented in Appendix A. These equations are developed from thin lens theory by letting the index of refraction approach infinity. These aberrations are identical to those developed from grating theory by other authors. As such, they are nothing new but they do indicate that the infinite index lens is probably a valid model

for a HOE. In Appendix A, third order aberrations are also developed for HOE's on spherical substrates.

A telescope design that employs HOE's is presented in Appendix D. This three-element system produces a completely color-corrected virtual image. This system could be of use if coupled with a small converging lens.

CHAPTER II

THE LENS ANALOGY

Holographic optical elements and lenses can perform similar functions, so it seems logical that they should both be describable in the same terms. In fact, for any one diffracted order, a thin holographic element can be considered as a "degenerate" lens, where the index of refraction approaches infinity and the curvatures and thickness approach zero such that the power of the element remains finite. Using this representation, systems containing refractive, reflective, and diffractive components can be designed using standard lens optimization codes.

In this chapter, the general lens equivalent of a holographic optical element is studied in detail. We then study a planar holographic lens consisting of a photographic plate exposed by two interfering spherical waves.

Holographic elements can also be made on curved surfaces. The exact lens analogy is presented for a general non-symmetric HOE.

Appendix A contains the first order theory and the third order aberrations for HOE's on both flat and spherical substrates. They are calculated using the lens

analogy and correlate exactly with those developed from grating theory.

Technique

To design a holographic lens system, we can simply design a system of lenses with the strange optical properties described in this chapter. No modification of existing lens optimization codes is required. A diffractive element is represented by a lens (or wedge) that is very thin compared with a wavelength of light and has a huge index of refraction.

For example, a Fresnel grating with a focal length of 100mm and a diameter of 20mm is equivalent to a plano-convex lens one-tenth of a wavelength thick (.05 μ m) with an index of 10,001.

The grating spacing which is the inverse of the spatial frequency is equal to the distance that must be spanned to give an optical path difference of a wavelength between the surfaces of the lens. Thus the spacing

$$S = \lambda / [d(OPD)/dr] = \frac{\lambda}{n(dt/dr)} \quad 2.1$$

where t is the lens thickness and r is the radial coordinate on the lens.

If the model is to be valid, the grating spacing represented by the model must appear the same to an off-axis ray bundle as it does to an on-axis bundle. This will

be the case if the optical path length (OPL) through the lens does not vary significantly with the angle of incidence. The OPL for a normal ray is $OPL_N = nt$. The OPL for an extreme off-axis ray, one with grazing incidence, is $OPL_G = nt \sec \theta$ where θ is the angle of refraction inside the lens. The angle θ can be determined from Snell's law, $n \sin \theta = \sin \pi/2 = 1$. For large n , $\sec \theta \approx 1 + 1/(2n^2)$. Thus the difference in OPL between grazing and normal incidence is

$$\Delta(OPL) = OPL_G - OPL_N \approx \text{thickness}/(2n) \quad 2.2$$

for the example given previously, the difference is negligible.

$$\Delta(OPL) \approx \lambda/200,000 \quad 2.3$$

This model describes the imaging properties of only the first diffracted order. Locations of other orders can be determined by substituting in integral multiples of the index of refraction; i.e., the second order can be located by doubling the index, the third order by tripling it, the minus-one order by substituting in minus the index, etc. Note also that a thin reflecting hologram has the same fringe spacing as a transmitting hologram of the same power and can be designed the same way when the system is unfolded.

The power of a holographic optical element is proportional to the wavelength of the illuminating light. Thus the index of refraction of the refractive model is proportional to the wavelength

$$(n - 1) = (n_0 - 1) \lambda / \lambda_0 \quad 2.4$$

The chromatic dispersion of the visible spectrum can be expressed as

$$D = \frac{n_f - n_c}{n_d - 1} = - \frac{\lambda_c - \lambda_f}{\lambda_d} \quad 2.5$$

where the subscripts refer to the c, d, and f spectral lines.

A word of caution: This analogy is geometrical, not physical and hence describes the location of the image but not the irradiance in it.

Planar Holographic Optical Elements

Holographic elements are normally exposed using two spherical waves as shown in Fig. 2.1. There is no loss of generality by choosing a local cartesian coordinate system such that z is normal to the hologram and the zx plane includes both spherical radiators.

Any planar hologram that is exposed using two interfering spherical waves can be exactly represented by two plano-convex lenses in contact where the convex surfaces are hyperboloids and the index approaches infinity. Each plano-convex lens is centered relative to its exposing point, $(x_1 \ 0 \ z_1)$ and $(x_2 \ 0 \ z_2)$, and not

Fig. 2.1. Hologram exposing geometry.

necessarily centered relative to one another. In Fig. 2.2 the lens equivalent is shown.

Figure 2.3 is an exploded view of the two-lens model. The lens on the left is hyperbolic-plano. It transforms the diverging spherical wave from point $(x_1, 0, z_1)$ into a plane wave propagating in the z direction. The plano-hyperbolic lens on the right transforms the plane wave into a spherically converging wave focusing at point $(x_2, 0, z_2)$. The hyperboloids are described by Stavroudis (1972):

$$y^2 + (x-x_1)^2 = (n_c^2-1)z^2 - 2(n_c-1)zz_1 \quad (\text{surface 1}) \quad 2.6$$

$$y^2 + (x-x_2)^2 = (n_c^2-1)z^2 + 2(n_c-1)zz_2 \quad (\text{surface 2}) \quad 2.7$$

These surfaces have vertex radii of

$$r_1 = (n_c-1)z_1 \quad 2.8$$

$$r_2 = (n_c-1)z_2 \quad 2.9$$

and conic constants

$$\kappa_1 = \kappa_2 = -[(n_c^2-1)-1] \quad 2.10$$

where n_c is the index associated with the constructing wavelength (λ_c) .

To test this theory, we traced some rays through a holographic optical element using diffractive theory (Offner, 1966). Then we represented the hologram as a lens and traced some rays through it. As the index of the lens

Fig. 2.2. Lens equivalent of holographic optical element.

Fig. 2.3. Exploded view of lens equivalent.

is increased, the focusing properties of the refractive model approach those of the hologram.

The construction geometry is shown in Fig. 2.1 where $(x_1 \ y_1 \ z_1) = (0 \ 0 \ 100)$ and $(x_2 \ y_2 \ z_2) = (10 \ 0 \ -100)$. The object to be imaged by the hologram was a point source located at $(x_3 \ y_3 \ z_3) = (-10 \ -10 \ 200)$. The particular ray to be traced passes through the hologram at a point $(x \ y \ z) = (0 \ -10 \ 0)$. Figure 2.4 shows the imaging geometry viewed normal to the hologram.

Rays of the two different colors were traced through the hologram: one wavelength was equal to the exposing wavelength ($\lambda_r = \lambda_c$). The other was of a longer wavelength ($\lambda_r = 1.5\lambda_c$). Table 2.1 contains the input parameters including the exposing indices of refraction (n_c), the curvatures (c_1 and c_2), and the conic constants (κ_1 and κ_2) calculated from Equations (2.8) to (2.10). The indices (n_r) were calculated from Equation (2.4). The ray positions (x_4 and y_4) on the Gaussian image plane (z_4) were found by tracing rays with a standard lens design computer program (Scientific Calculations, Inc., 1970).

The results tabulated in Table 2.1 show that as the index of refraction becomes large, the model approaches the true solution predicted by diffraction theory.

Fig. 2.4. Geometry of holographic imaging system; hologram in x - y plane.

Table 2.1. Ray tracing comparison of lens analogy with HOE

Exposing geometry			Reconstruction wavelength					
			$\lambda = \lambda_o$			$\lambda = 1.5\lambda_o$		
			Image plane					
			$z_4 = 66.6667$			$z_4 = 40.000$		
n_o	$c_1=-c_2$	$\kappa_1=\kappa_2$	n	x_4	y_4	n	x_4	y_4
11	.001	-119	11	10.274	3.686	16	8.540	2.800
101	.0001	-10200	101	10.253	3.664	151	8.505	2.760
1001	.00001	-1,002,000	1001	10.251	3.662	1501	8.502	2.756
Diffraction theory				10.251	3.662		8.501	2.756

Hologram on a Spherical Surface

When we studied the lens equivalent of a hologram on a plane surface, the "lens" was considered to be two hyperbolic plano-convex lenses. One transformed the diverging spherical wave into a plane wave, and the second changed the plane wave into a converging spherical beam.

A hologram on a spherical surface can be viewed in somewhat the same manner. In Fig. 2.5, the spherical surface is curve (h,i,j) centered at (c). Once again we assumed two lenses; the front lens (a,e,j,i) and the rear lens (b,f,j,i,h). At the exposing geometry the front lens produces an image of (d) at the center of curvature (c). Hence, its axis of symmetry is line (d,a,i,c). The rear lens reimages the image from point (c) to point (g). The axis of symmetry of the rear lens is line (h,b,c,g).

Surfaces (ae) and (bf) are Cartesian ovals (Stavroudis, 1972). The thicknesses of these two lenses, measured radially about point (c) are ϵ_1 and ϵ_2 , defined by

$$(n_c^2 - 1)\epsilon_1^2 + (n_c - 1)(r + \ell_1)2\epsilon_1 + 4r\ell_1 \sin^2\left(\frac{\theta_1}{2}\right) = 0 \quad (2.11)$$

$$(n_c^2 - 1)\epsilon_2^2 - (n_c - 1)(r + \ell_2)2\epsilon_2 + 4r\ell_2 \sin^2\left(\frac{\theta_2}{2}\right) = 0 \quad (2.12)$$

Equivalent Lens Surfaces Resulting
from Spherically Aberrated Waves

The simple optical systems shown in Fig. 1.1 will construct HOE's as described above. In some applications, the inherent spherical aberration will be tolerable. If the image quality requirements on the system are stringent, a different amount of spherical aberration may be necessary. Hence, the HOE's may have to be constructed with spherically aberrated beams.

The amount of aberration and methods of generating it will be considered in Chapters III, IV, and V.

A spherically aberrated wavefront varies from a spherical wavefront as shown in Fig. 2.6. A positive wavefront error is in front of the reference sphere and gives rise to positive spherical aberration in the convention of Hopkins (1950) and Welford (1974). The wavefront error $W(y)$ is of the form

$$W(y) = Py^4 + Qy^6 + Ry^8 \quad (2.13)$$

where P , Q , and R are constants and y is the aperture variable shown in Fig. 2.6. A purely spherical wavefront requires a hyperbolic surface [Eq. (2.6)] on the HOE-equivalent lens. A spherically aberrated wavefront requires a refracting surface whose sag is

$$z_1 = c_1 y^2 \{1 + [1 - (\kappa_1 + 1) c_1^2 y^2]^{1/2}\}^{-1} + Dy^4 + Ey^6 + Fy^8 \quad (2.14)$$

Fig. 2.6. Aberrated wavefront (dotted line) and reference sphere (solid line).

where

$$D = P / (n_c - 1)$$

$$E = Q / (n_c - 1)$$

$$F = R / (n_c - 1)$$

Here is the real power of the lens analog. A lens designer adds aspheric terms to lens or mirror surfaces. By adding aberrations to given elements, the image quality of the system can be improved. Similarly, HOE's can be constructed with aberrated waves. Adding the aberration to given elements can improve the system's overall image quality.

A HOE can be represented as a plano-convex (concave) lens whose curvature and aspheric coefficients can be varied along with the rest of the lenses and mirrors when the image quality of the system is optimized. This truly produces a "globally" optimized system.

How can such a HOE be constructed? For a thin HOE, only the fringe spacing along the surface of the HOE is important. The fringe tilt does not matter. Hence one of the constructing wavefronts can be chosen for convenience (a plane or spherical wavefront or the output of a convenient lens) and then the other wavefront will have to be aberrated to give the correct fringe spacing.

The most straightforward method (one of several) of determining the shape of the aberrated wavefront,

knowing the shape of the equivalent lens, is to use Equation (2.1) to determine the fringe spacing (S) at several points on the HOE (4 or more). This fringe spacing is produced by two interfering wavefronts; one known (chosen for convenience), and one that is the unknown aberrated wavefront. Using the grating equation

$$\sin \theta'_c = \lambda_c / S - \sin \theta_c \quad (2.15)$$

and knowing the normal angle of a ray from one of the constructing beams (θ_c) we can calculate the other (θ'_c). If we calculate the incident angle (θ'_c) of the constructing wavefront on the HOE at several points, we can describe the constructing wavefront fairly well. As a result, we can also design optics to generate this aberration as described in Chapter V.

To design thick HOE's, we proceed the same except that we cannot choose one constructing beam for convenience. We must aberrate both to give the correct fringe spacing and angle at several points on the HOE.

Conclusions

The validity of the model is demonstrated by the ray trace data in Table 2.1. Also, the first and third order properties developed in Appendix A from lens theory match those developed from grating theory.

With this scheme a designer can design a holographic system composed of elements that are exposed using

two spherical beams. He need only specify the conic constants for the surfaces, Eq. (2.10). The two surface curvatures can be adjusted by the computer. Another variable the designer has at his disposal is the element's spherical aberration. It can be used to help balance the aberrations of the total optical system.

The aberrations for some special cases are presented. The image quality for a more general case can be determined by tracing "real rays" through the system using the lens model presented here.

To summarize the design procedure, standard lens design codes can be used. The designer should start optimizing his optical system using indices of about 11 (a convenient choice since $n-1 = 10$) for the holographic elements. This avoids numerical sensitivity problems. When the design has been optimized, increase the indices to about 101 and reduce the curvatures to gain the same powers. The conic constants will also have to be updated. When the design once again converges, increase the index again. Repeat the process until the thickness of each holographic element is small relative to a wavelength or the power of each of the surfaces does not change appreciably when the index is changed. Finally, one must calculate the exposing geometry (z_1 and z_2) from Eqs. (2.8) and (2.9).

CHAPTER III

DESIGNING THICK TRANSMITTING HOLOGRAPHIC OPTICAL ELEMENTS

To balance the third order aberrations in an optical system, a designer must be able to prescribe the amount of third order spherical aberration in each element. With thin holographic optical elements (HOE) any combination of third order spherical aberration and focal length can be achieved by simply varying the exposing conjugates (Latta, 1971). With thick HOE's, we have additional constraints. To maximize the element's efficiency, the Bragg condition must be met over the aperture. That is, the fringes in the emulsion must be tilted at the Bragg angle. The fringe tilt is determined by the construction conjugates and the changes in the emulsion's thickness and index of refraction during processing.

Holograms are normally constructed by interfering two spherical beams in the film plane. The positions of the two point sources are the only variables and we have three conditions: the power, the spherical aberration requirements, and the Bragg condition. Hence, the image quality must be sacrificed.

We would like to suggest constructing the hologram which spherically aberrated beams. If we introduce third

order spherical aberration into both beams, we have four variables at our disposal; the distances from each exposing center to the film plate (z_c and z'_c) and the amount of third order spherical aberration in each beam (S_c and S'_c). (The "c" subscripts refer to "construction," "r" will be used for "reconstruction.") By proper selection of these four variables, we can construct a hologram with the proper power and the desired amount of third order spherical aberration. We can also meet the Bragg condition in the paraxial region and in the region where the third order variations are the dominant error. This level of sophistication in design will produce "excellent" imagery for rays diffracted at 20° or less, and "much improved" imagery for larger cone angles.

In the following section, the positions of the exposing centers are theoretically determined. The third order spherical aberration needed in each beam is calculated in Appendix A. Finally, the value of this approach is experimentally demonstrated.

Derivation

The thickness of the emulsion is assumed to change from t_c during construction of the HOE to t_r after the hologram is developed. The average index of refraction is assumed to change from n_c at the construction wavelength

to n_r after the developing at the reconstructing wavelength.

We will also assume that the two exposing points used to construct the HOE are on the center line of the system. (Note that the system's aperture may be off axis.) We also require the HOE to be normal to the center line.

For the holographic optical element that is to go in the optical system, we assume that the reconstruction object and image distances (z_r and z'_r in Fig. 3.1) and the spherical aberration desired in both the object and image beams (S_r and S'_r) are known from a thin HOE design. We need to find the conjugates (z_c and z'_c) at which to construct the HOE. We also need to calculate the third order spherical aberration that must be introduced into each exposing beam (S_c and S'_c). We shall begin by determining the paraxial variables, z_c and z'_c .

We have two conditions that we wish the HOE to meet in the paraxial region; we want to specify the power of the element and we want to satisfy the Bragg condition. The power of the element was determined by Champagne (1967):

$$\begin{aligned} 1/z'_c - 1/z_c &= A \\ A &= \lambda_c/\lambda_r [1/z'_r - 1/a_r] \end{aligned} \quad (3.1)$$

In order to optimize the efficiency in the paraxial region, we must calculate the ideal Bragg angle, α_r , as shown in Fig. 3.2. From the reconstruction Bragg angle,

Fig. 3.1. Desired wavefront geometry.

Fig. 3.2. Ray passing through a thick emulsion.

α_r , we can calculate the Bragg angle during construction α_c (taking emulsion shrinkage and index variation into account). Knowing the constructing Bragg angle α_c , we can write another expression involving the exposing conjugates (z'_c and z_c). Thus we can generate a second relationship between z_c and z'_c . Therefore, we can solve for z_c and z'_c .

As shown in Fig. 3.2, the reconstruction beam is refracted at the front surface of the hologram (Eq. [3.2]), reflected off of the "Venetian Blind" inside [Eq. [3.3]], and refracted at the rear surface (Eq. [3.4]).

$$\sin \theta_r = n_r \sin B_r \quad (3.2)$$

$$\alpha_r = 1/2(B'_r + B_r) \quad (3.3)$$

$$\sin \theta'_r = n_r \sin B'_r \quad (3.4)$$

In the paraxial region, all of the angles in Eqs. (3.2) and (3.4) are small so $\sin \theta_r \approx \theta_r \approx y/z_r$. Thus Eqs. (3.2) to (3.4) can be solved together giving the reconstructing Bragg angle

$$\theta_r = \frac{y}{2n_r} (1/z_r + 1/z'_r) \quad (3.5)$$

The emulsion thickness may change during processing which would cause the Bragg angle to change also. Assuming a linear shrinkage perpendicular to the plane of the hologram, we can write the relationship

$$t_c \tan \alpha_c = t_r \tan \alpha_r \quad (3.6)$$

Equation (3.6) was experimentally validated as will be discussed later.

In the paraxial region, α will be small as can be seen in Fig. 3.2. Hence, we can use the approximation $\tan \alpha \approx \alpha$. Thus in the paraxial region, Eq. (3.6) can be reduced to linear form

$$t_c \alpha_c \approx t_r \alpha_r \quad (3.7)$$

Refraction equations and Bragg "reflection" equations similar to Eqs. (3.2) to (3.4) can be written to describe the Bragg angle during construction. They lead to a Bragg angle similar to Eq. (3.5)

$$\alpha_c = y/2n_c (1/z_c + 1/z'_c) \quad (3.8)$$

We can now relate Bragg angles during construction (Eq. [3.8]) and reconstruction (Eq. [3.5]). Thus

$$\begin{aligned} 1/z_c + 1/z'_c &= B \\ B &= \frac{n_c t_r}{n_r t_c} (1/z_r + 1/z'_r) \end{aligned} \quad (3.9)$$

Using A (Eq. [3.1]) and B (Eq. [3.9]), we can solve for the exposing conjugates

$$\begin{aligned} 1/z'_c &= 1/2 [A + B] \\ 1/z_c &= 1/2 [B - A] \end{aligned} \quad (3.10)$$

We have determined the paraxial variables (z_c and z'_c). The third order variables, the spherical aberration

to be introduced into each exposing beam (S_c and S'_c) are calculated in a similar manner in Appendix B.

The exposing centers (z_c and z'_c) and the spherical aberration in each beam (W_c and W'_c) are all positive quantities as drawn in Fig. 3.1. The arcs are reference spheres and the dotted lines represent the aberrated wavefront.

From Appendix B the third order spherical aberration to be introduced into each exposing beam is measured in mm. The wavefront deviations from the reference spheres centered at the paraxial foci and tangent to the HOE are

$$W'_c = 1/8 S'_c \frac{(x^2+y^2)^2}{h_o^4}$$

and

$$W_c = 1/8 S_c \frac{(x^2+y^2)^2}{h_o^4} \quad (3.11)$$

where x and y are aperture coordinates and h_o is the radius of the aperture.

$$S_c = 1/2 (E+D)$$

$$S'_c = 1/2 (E-D)$$

(3.12)

$$D = \frac{\lambda_c}{\lambda_r} (S_r - S'_r) + h_o^4 \left\{ \frac{\lambda_c}{\lambda_r} [(z_r)^{-3} - (z'_r)^{-3}] + (z'_c)^{-3} - (z_c)^{-3} \right\}$$

$$\begin{aligned}
E = \frac{t_r n_c}{t_c n_r} (S'_r + S_r) + h_o^4 \left\{ \frac{t_r n_c}{t_c n_r} \left[\left(1 - \frac{1}{3n_r^2}\right) [(z'_r)^{-3} \right. \right. \\
\left. \left. + (z_r)^{-3}] \right. \right. \\
- \frac{1}{6n_r^2} [1 - (t_r/t_c)^2] [1/z'_r + 1/z_r]^3 \Big] \\
- \left(1 - \frac{1}{3n_c^2}\right) [(z'_r)^{-3} + (z_c)^{-3}] \Big\}
\end{aligned}$$

Experimental Verification

A transmitting holographic optical element was constructed to verify this work. It was constructed with an Argon laser (514.5nm) so as to be stigmatic ($S_r = S'_r = 0$) when reconstructed with a HeNe laser (632.8nm). The film used was "dichromated gelatin." It was made from Kodak 649F plates sensitized with 3.5% ammonium dichromate solution as described by McCauley, Simpson, and Murback (1973).

The refractive index of the emulsion was found to change from $n_c = 1.5722$ at 514.5nm to $n_r = 1.53$ at 632.8nm after processing. The indices were determined using an Abbé refractometer and index matching respectively.

The thickness was determined indirectly. The maximum amount of power is diffracted when the Bragg condition is met. This gives the change of thickness assuming the tangent relationship of Eq. (3.6). The thickness was found to increase by $13. \pm 1. \%$. The tangent relationship gave consistent results for a range of fringe angles

between 4.4° and 11° , and for fringe spacings over the range $1.1\mu\text{m}$ to $3.0\mu\text{m}$ at both 632.8 and 514.5nm (10 data points). These data tend to validate the tangent relationship for dichromated gelatin as Vilkomerson and Bostwich's (1967) work did for standard Kodak 649F absorption holograms.

The hologram was constructed so that it would change a collimated beam into a converging spherical beam at $\lambda_r = 632.8\text{nm}$ as shown in Fig. 3.3. This hologram was constructed at $\lambda_c = 514.5\text{nm}$ using the system shown in Fig. 3.4. The first and third order calculations (Eqs. [3.10] and [3.11]) suggested paraxial foci located at $z_c = 1143\text{mm}$ and $z'_c = 202.4\text{mm}$ from the film with third order spherical components of $S_c = 1.615\text{mm}$ ($h_o = 100\text{mm}$) and $S'_c = -.345\text{mm}$ ($h_o = 100\text{mm}$). The negative third order spherical aberration was generated by putting a 2mm thick plane parallel plate (ppp) in the small f/number (fast) beam. The plane parallel plate has almost no effect on the other beam because it has such a large f/number (slow beam). The slow beam needs positive spherical aberration. It was achieved by imaging the aberrations of a plano-convex lens on the film plane with an Offner (1963) field lens. Two available lenses had approximately the right focal lengths. Their curvatures were fed into a lens design computer code that selected the element spacings to give the aberration needed. The final geometry is shown in Fig. 3.4.

Fig. 3.3. Reconstruction geometry: $\lambda_r = 632.8\text{nm}$ -- HOE changes the collimated beam to a spherical converging beam.

Fig. 3.4. Constructing geometry -- BS= beamsplitter; S = spatial filter; HOE has emulsion on left; ppp is a 2mm thick plane parallel plate; L_1 generates aberration; $f_l = 78\text{mm}$; $\text{dia} = 50\text{mm}$; L_2 is field lens; $f_l = 308\text{mm}$.

The point spread function for the HOE is shown in Fig. 3.5a. It has a dimension of $40\mu\text{m}$ resulting from aberrations higher than third order. By contrast, if one uses unaberrated spherical constructing waves and matches the Bragg condition in the center of the aperture, the minimum size of the point spread function is $300\mu\text{m}$, as shown in Fig. 3.5b.

Conclusions

The image quality of a high efficiency thick holographic optical element can be significantly improved by constructing it with spherically aberrated waves. We have demonstrated an eight-fold increase in resolution with a very crude aberration generating system and off-the-shelf lenses. Much better performance should be realizable given the need.

(a)

Fig. 3.5. Point spread function of (a) corrected HOE at 632.8nm and (b) uncorrected HOE exposed with point sources.

(b)

Fig. 3.5.--Continued

CHAPTER IV

DESIGNING THICK REFLECTING HOLOGRAPHIC OPTICAL ELEMENTS

Thick reflecting holographic optical elements (HOE) are normally constructed by interfering two spherical beams of light that approach the film from opposite directions. The locations of these point sources (exposing conjugates) are chosen to give the correct power for the element and to optimize its efficiency.

If the reconstruction wavelength is different from the construction wavelength, the power of the HOE changes and the image will show spherical aberration as described by Champagne (1967) and Latta (1971). A reduction of the Bragg efficiency at the edge of a HOE can also result if the index of refraction of the emulsion changes substantially during the processing.

These problems can be avoided if the HOE is constructed using spherically aberrated beams. In this paper we describe the amount of third order spherical aberration required in the constructing beams and how to introduce it. We conclude with a numerical example.

The exposing geometry is shown in Fig. 4.1. All angles and distances are positive as drawn. Such a system produces fringes in the emulsion that are roughly parallel

Fig. 4.1. HOE construction geometry showing the spherical aberration W_c and W'_c and the resulting wavefront tilt γ'_c and γ_c .

to the surfaces as depicted in Fig. 4.2. During construction these fringes are almost exactly a half wavelength apart, (λ_c/n_c) . The same must be true during reconstruction (at λ_r/n_r) to meet the Bragg condition (Collier, Burchart, and Lin, 1971). The number of fringes through the thickness is m where

$$m = \frac{t_c}{r_c/\lambda_c} = \frac{t_r}{n_r/\lambda_r}$$

or

$$t_c/t_r = \frac{\lambda_c/n_c}{\lambda_r/n_r} \quad (4.1)$$

The subscripts "c" and "r" denote construction and reconstruction.

If the thickness ratio is met, then in the paraxial region the Bragg angle condition is met automatically. Thus any pair of exposing conjugates (z_c and z'_c in Fig. 4.1) that produce the desired element power will also match the Bragg angle condition in the paraxial region. For larger aperture systems that diffract the light by up to 20° , the third order spherical aberration and the third order variation of Bragg angle are the only significant errors. They can both be optimized by choosing the correct pair of exposing conjugates (z_c and z'_c) and the correct sum of spherical aberration coefficients [$(S_c + S'_c)$ in Fig. 4.1].

Fig. 4.2. Constructing beams interfering in the emulsion.

Construction Parameters

A thick reflecting holographic optical element can be constructed that has the correct power and the right amount of third order spherical aberration if the following formulae are employed. Also the Bragg conditions will be optimized to third order assuming the thickness requirement (Eq. [4.1]) is met.

$$\begin{aligned}
 1/z'_c \text{ \& } 1/z_c = 1/2 \{ \lambda_c/\lambda_r (1/z'_r + 1/z_r) \\
 \pm [2(n_c/n_r)^2 [(z'_r)^{-2} + (z_r)^{-2}] - (\lambda_r/\lambda_r)^2 \\
 [1/z'_r + 1/z_r]^2]^{1/2} \}
 \end{aligned} \tag{4.2}$$

$$\begin{aligned}
 S_c + S'_c = \frac{\lambda_c}{\lambda_r} (S_r + S'_r) + h_o^4 \{ \frac{\lambda_c}{\lambda_r} [(z'_r)^{-3} + (z_r)^{-3}] \\
 - (z'_c)^{-3} - (z_c)^{-3} \}
 \end{aligned} \tag{4.3}$$

The paraxial point sources (z_c and z'_c) are shown in Fig. 4.1. The spherical aberration coefficients (S_c and S'_c) for the constructing wavefronts are related to the wavefront errors by $W_c = 1/8 S_c (x^2 + y^2)^2 / h_o^4$ and $W'_c = 1/8 S'_c (x^2 + y^2)^2 / h_o^4$ where h_o is the aperture height and (W_c and W'_c) are measured in mm (Hopkins, 1950). Positive wavefront errors from the reference spheres are shown in Fig. 4.1. The reconstruction geometry is identical (z_r , z'_r , S_r , and S'_r). The indices of refraction of the emulsion before and after processing are (n_c and n_r).

Equations (4.2) and (4.3) are derived in Appendix C. Equation (4.2) gives the location of the point sources with which we construct the hologram and Eq. (4.3) is the combined amount of spherical aberration required in the two beams.

The quantity under the radical in Eq. (4.2) must be positive. Therefore, we have a condition on the constructing wavelength

$$\frac{\lambda_c/n_c}{\lambda_r/n_r} \leq \sqrt{2 \frac{(1+z'_r/z_r)^2}{1+(z'_r/z_r)^2}} \quad (4.4)$$

This function is plotted in Fig. 4.3.

At first glance, this seems to indicate that the reconstruction wavelength must be about the same as the constructing wavelengths or longer. However, if the Bragg condition is met at one wavelength, it will also be met by radiation with half the wavelength, a third the wavelength, and other unit multiples.

Experimental Verification

A thick reflecting HOE was constructed with the following requirements:

$$\begin{aligned} z_r &= \infty \\ z'_r &= 205\text{mm} \\ \lambda_r &= 514.5\text{nm} \\ S_r &= S'_r = 0 \end{aligned}$$

Fig. 4.3. Maximum construction wavelength vs. image magnification.

It was constructed at $\lambda_c = 488\text{nm}$ in dichromated gelatin as described by McCauley et al. (1973). When the stripped Kodak 649F plates were sensitized in a 5% ammonium dichromate solution, the thickness condition, Eq. (4.1), was met after two days drying time. The indices of refraction before and after processing were determined using an Abbé refractometer ($n_c = 1.58$ at 488nm and $n_r = 1.54$ at 514.5nm). From this input, Eqs. (4.2) and (4.3) give the construction geometry.

$$z_c = 2740\text{mm}$$

$$z'_c = -201\text{mm}$$

$$S_c + S'_c = 5.1 \times 10^{-3}\text{mm at } h_o = 25\text{mm}$$

The optical system shown in Fig. 4.4 gives the required conjugates and spherical aberration. The point spread function at the reconstruction wavelength is shown in Fig. 4.5. Its size is attributable to variations in the thickness of the film plate and gelatin. No spherical aberration is evident as the point spread function is examined through focus.

Conclusions

A design procedure has been developed that can improve the imaging properties of thick reflecting holographic optical elements. A more complicated optical system is required to construct the HOE's. However, the

Fig. 4.4. Optical system to construct 205mm f.l reflecting HOE -- S = spatial filter; HOE = 649F plate, emulsion on right; Plano convex lens introduces aberration $f_l = 1000\text{mm}$, $n = 1.523$.

Fig. 4.5. Point spread function of HOE at 514.5nm --
Size $\approx 100\mu\text{m}$.

procedure does allow the optical designer more control of the aberrations in his optical system.

CHAPTER V

CONSTRUCTING THICK HOLOGRAPHIC OPTICAL ELEMENTS

This chapter contains the engineering details necessary to construct a thick holographic optical element using aberrated beams. The optical quality of the substrate is discussed and a testing procedure is described. The index of refraction and thickness of the emulsion must be known for both the unprocessed and processed film and methods are described for index determination. The last half of the chapter describes how to design an optical system that will produce a given spherical beam that has a prescribed amount of spherical aberration. This includes a thin-lens, third-order design scheme to find the region of solution and a description of how to optimize the construction system using "real rays" traced by a computer code.

Details About the Emulsion and Substrate, Thickness of the Substrate

Random variations in the thickness of the substrate and emulsion together affect the image quality of both transmission and reflection HOE's. Small amounts of plate warpage do not affect the image quality. (Warpage errors cancel out during reconstruction.)

Variations in the thickness of the substrate produce a wavefront error in any light beam passing through it:

$$W(x,y) = (n - 1)t(x,y) \quad (5.1)$$

(Gara and Yu [1971] present this equation for emulsion thickness.) A transmission HOE is constructed with both beams passing through the substrate or else neither passing through. The reconstruction beam makes one pass so the thickness error will degrade the optical quality in either case. A thick reflection HOE is constructed with beams coming from both sides of the film so one must pass through the substrate introducing the thickness errors.

Small amounts of wedge or power in the substrate can be compensated and so are of little concern. Loss of image quality results from random thickness variation and cylinder.

Figure 5.1a shows a simple scheme for determining minor thickness variations. The substrate and emulsion together are placed in a collimated beam of monochromatic light. The reflections off of the outer surfaces will coherently interfere. The difference in thickness between two adjacent fringes is

$$\Delta t = \lambda/2n \quad (5.2)$$

Figure 5.1b is an example of the interference pattern seen in a Kodak 649F plate. The roughly equally spaced straight fringes show wedge. The change in spacing and lack of

(a) Optical system

Fig. 5.1. Thickness variation of substrate.

(b) Example of fringes

Fig. 5.1.--Continued

straightness result from random thickness variations superimposed on the wedge. This kind of interferogram can be analyzed by subtracting a linear term (the tilt) and then the quadratic term (the power). What remains will be the wavefront error of the HOE. (This is a common analysis performed in interferometric optical testing.)

Index of the Emulsion

The index of refraction of a film usually changes during the processing. This was pointed out by Bryngdahl (1972) who presents indices for some common photographic plates. Similarly, this author found significant changes due to processing in the index of dichromated gelatin.

The index of refraction of the emulsion can be determined by several methods. Two of the simplest employ the Abbé refractometer and index matching.

The Abbé refractometer is the easiest method and will be described first. If a thick emulsion ($t \gg \lambda$) has a lower index than its substrate, then the Abbé can be used in transmission as described by Longhurst (1967, p. 87) and Bausch and Lomb (n.d.). Figure 5.2 shows the essential components of an Abbé refractometer being used in reflection. The white light enters the high index glass from the bottom and is reflected off of the substrate/emulsion interface and the index matching oil/emulsion

Fig. 5.2. Abbé refractometer showing interference between the two reflections.

interface. With a thin emulsion, these two beams will interfere, giving dark fringes for certain angles (θ).

In the Bausch and Lomb manual on their "Abbé 3L" refractometer, A. Francis Turner (1977) describes a method of determining both the index of refraction and thickness of a thin transparent coating when the coating has a lower index of refraction than the substrate. We had to extend his idea to the case where the coating has a higher index than the substrate. The emulsion's index, thickness, and dispersion are:

$$\begin{aligned} n_d &= [(9n_1^2 - n_2^2)/8]^{1/2} \\ t &= \lambda_d [2/(n_1^2 - n_2^2)]^{1/2} \\ n_f - n_c &= 1/n_d \{ \lambda_d (\lambda_f - \lambda_c) / (4t^2) + n_1 (n_f - n_c)_{\text{apparent}} \} \quad (5.3) \end{aligned}$$

where n_1 and n_2 are the dark bands of lowest apparent index of refraction.

This method is convenient and easy when it works. However, there are some shortcomings. If the emulsion is too thick, the lines n_1 and n_2 are very close together reducing the accuracy of the thickness measurement ($t > 20\mu\text{m}$). Several factors can reduce the visibility of the fringes. These include variations of the emulsion thickness, absorption in the emulsion, and too little light reflected off of the emulsion-substrate interface because of a small difference of refractive index.

The index matching method is messy and crude, but it always works. It requires an index matching tank, also known as a liquid gate. Several index matching oils must be found, such as oil of cloves ($n \approx 1.56$), motor oil ($n \approx 1.49$), silicon based oils ($n \approx 1.52$), and the Cargile oil used with the Abbé refractometer ($n \approx 1.625$). The index of the oils can be determined exactly on the Abbé refractometer.

The film index is determined as follows: Cut a trench in the emulsion with a sharp knife, sloping the sides as much as possible as shown in Fig. 5.3a. Then immerse the film in the liquid gate. Put this in a Mach-Zehnder interferometer as shown in Fig. 5.3b. Figure 5.3c shows a quarter wave of error. To find out whether the trench has less or more optical thickness than the emulsion, we must push on one of the mirrors to shorten one of the optical paths.

Thickness of the Emulsion

The thickness of the sample can be determined using either the Abbé refractometer scheme described above or a Michelson type microscope objective that compares the heights of the object (Fig. 5.3a) with a reference flat using a low pressure mercury light source (has several bands). For example, see the Leitz (1973) catalog.

Fig. 5.3. Index matching (a) trench cut in emulsion; (b) Mach-Zehnder interferometer (BS = beam splitter, LG = liquid gate, I = image); (c) example image showing $OPD = \pm \lambda/4$.

For an emulsion that contains a thick reflection HOE, the wavelength at which we see the greatest reconstruction efficiency will give the change of thickness via Eq. (4.1).

Optical Systems to Construct HOE's

Holographic optical elements are commonly constructed with two spherical beams of light. Latta (1971) shows that with thin HOE's, the element's power can be specified and the spherical aberration can be balanced at one point in the aperture. With thick HOE's, the fringe tilt in the emulsion must also be specified. Hence, we need other degrees of freedom; namely, spherical aberration in the constructing beams.

In this section we will describe how to design a system of lenses to produce an aberrated beam. The process of design involves first choosing the general type of optical system that will generate either positive or negative spherical aberration on either a converging or diverging beam (Fig. 5.4). We then describe a thin-lens design scheme that will produce the desired aberration from plano convex or plano concave lenses. (In some instances more complex lens systems may be required.) Finally, we should balance out higher order aberrations and "fine tune" our design with a lens optimization computer program. This also acts as a check on our approximate solution.

Fig. 5.4. Systems producing third order spherical aberration -- (a) $+W_c$ & $+Z_c$; (b) $-W_c$ & $+Z_c$; (c) $+W_c$ & $-Z_c$; (d) $-W_c$ & $-Z_c$; S = spatial filter; L_1 = aberration generating lens; L_2 = imaging lens; O = corrected telescope objective.

Fig. 5.4.--Continued

Positive spherical aberration on a diverging beam as shown in Fig. 2.6 is relatively easy to produce and image onto the film plane. Positive spherical aberration is produced by any converging (or positive) lens with a real object and image. Such a system is shown in Fig. 5.4a. Negative spherical aberration on a diverging beam is somewhat more difficult to produce. The system shown in Fig. 5.4b requires two good quality small f/number telescope objectives to give an aberration-free converging beam in addition to lenses L_1 and L_2 .

Spherical aberration riding on a converging beam can be produced by putting the aberration generating lens nearly in contact with the film as shown in Figs. 5.4c and 5.4d. A lens to be used in contact will have to be specially made to fit the given HOE requirements and it must be anti-reflection coated to avoid spurious reflections. By contrast, the imaging systems shown in Figs. 5.4a and 5.4b have spacings t_1 , t_2 , and $t_3 \approx z_c$ that can be adjusted to allow the use of lenses whose focal lengths are only approximately correct. The lenses L_1 and L_2 are also a long way from the film so the beams reflected off of them will be attenuated. Note that a small amount of negative spherical aberration can be generated by passing a converging or diverging beam through a plane parallel plate.

How do we choose the lenses to produce the aberrated wavefront? The field lens L_2 simply images the aberration generated by L_1 onto the film as described by Offner (1963). Its focal length must be roughly $f \cong (1/t_2 + 1/t_3)^{-1}$ but its shape is unimportant. The lens L_1 must produce the correct paraxial angle (u) (Fig. 5.5) and the correct amount of third order spherical aberration (W_C). Choosing a plano-convex (or plano-concave) lens for L_1 allows a great deal of variation in the spherical aberration generated. For the system shown in Fig. 5.5 the lens size can be determined from the following equation:

$$\begin{aligned}
 F(x) &\equiv S_C h_\ell (z_C/h_O)^3 = 2[(G_1 x - G_3)x + G_6]x \\
 x &= \phi h_\ell / [(n-1)u] = \Delta u / [(n-1)u] \\
 G_1 &= n^2(n-1)/2 \\
 G_3 &= (3n+1)(n-1)/2 \\
 G_6 &= (3n+2)(n-1)/2n
 \end{aligned} \tag{5.4}$$

This relationship results from equating the spherical aberration needed to that of a plano-convex lens using Smith's (1966) equation (10.9M) where S_C and z_C are the spherical aberration coefficient and paraxial focus of one of the constructing beams of a HOE. The aperture radius of the HOE and lens are h_O and h_ℓ . The power of the lens ϕ times the aperture height h_ℓ equals the paraxial angle change (Δu as shown in Fig. 5.5). Thus if $t_1 = \infty$,

(a)

(b)

Fig. 5.5. Sign convention for aberration generation scheme -- (a) imaging geometry; (b) lens in contact.

then $(\Delta u = u)$ so $x = 1/(n-1)$; or if $t_1 = t_2$, then $x = 1/2(n-1)^{-1}$. Equation (5.4) is plotted in Fig. 5.6 along with another function $G(x)$, obtained by multiplying both sides of Eq. (5.4) by x .

We now have the tools to choose the right lens for a given application. If we have a lens in contact (Figs. 5.3c and 5.3d), we know S_c , z_c , and $h_\ell = h_o$. So we find $F(x) = S_c/y (z_c h_o)^3$ on the ordinate of Fig. 5.6 and read off x on the abscissas giving us the required power of the lens.

If we are imaging the aberration onto the film we have more latitude in the selection of the lenses. First consider positive spherical aberration on a diverging beam. As can be seen in Fig. 5.5, the angle change $(\Delta u = \phi h_\ell)$ can reasonably lie in the range of $1.1u < \Delta u < 10u$. Similarly, when we have negative spherical on a diverging beam as shown in Fig. 5.3b, a reasonable range of values might be $0.1u < (-\Delta u) < 0.9u$. We can determine lens powers $(\phi_{\min}$ and $\phi_{\max})$ associated with these extremes in Δu . Each of these powers has an edge ray height (h_ℓ) associated with it. All of these quantities can be found as outlined in Fig. 5.7a. The next step is to find a plano-convex or plano-concave lens "on the shelf" whose power ϕ is between $\phi_{\min}$ and $\phi_{\max}$, and whose radius (h_ℓ) seems larger than required.

Fig. 5.6. Functions $f(x)$ [Eq. (5.4)] and $g(x)$ for $n = 1.52$.

Fig. 5.7. Flow charts -- (a) given a reasonable range of Δu find the range of lens powers and radii (ϕ & h_l) that will produce the aberration coefficient S_c ; (b) when a specific lens with power ϕ ($\phi_{\min} < \phi < \phi_{\max}$) is chosen, is its radius greater than that required (h_l)?

The procedure outlined in Fig. 5.7b calculates the minimum necessary radius (h_ℓ) for a given lens power (ϕ) and the inter-element spacings (t_1 and t_2) as shown in Fig. 5.5.

Thus far, the system has been designed to third order. We have ignored element thicknesses and higher order aberrations both in the HOE and in the lenses. We have chosen the lenses (L_1 and L_2) that we intend to use. By using a lens design computer code, we can "tune" the system further by adjusting the inter-element spacings (t_1 , t_2 , and t_3).

If we are making a transmission HOE, we must aberrate both constructing beams separately. A simple method of optimizing the system is as follows. At three to five aperture heights, calculate the ideal fringe spacing and tilt α_r on reconstruction (see Collier et al., 1971, p. 228). Then using Eq. (3.6):

$$t_c \tan \alpha_c = t_t \tan \alpha_r$$

we can calculate the change in fringe tilt resulting from processing. We now know the fringe angles during construction as well as the fringe spacing, which does not change during the processing. These two conditions specify the ideal construction ray angles. Thus we can determine the ray heights and angles for several real rays. These rays can be traced backward through the aberration

generating system. The heights of the rays at the spatial filters are the errors to be minimized.

An aberration generation system for reflecting HOE's is easier to optimize than one for transmitting HOE's. We do not have to calculate the constructing ray angles at several positions in the aperture. Instead, we trace rays through a HOE-equivalent lens and then backward through the aberration generating system. As example is shown in Fig. 5.8. The desired reconstruction geometry and equivalent lens are shown in Figs. 5.8a and 5.8b. The constructing geometry is shown in Fig. 5.8c, which was determined from Eqs. (4.2) and (4.3). A system to construct the reflecting HOE can be seen in Fig. 5.8d. We use two objectives to produce the converging beam. The other beam includes lens L_1 to create the aberration and lens L_2 to project it onto the film. Figure 5.8c shows the computer model. Note that the system has been "unfolded" and light is diverging from a position $(-z_c)$ rather than converging toward $(+z_c)$ as shown in Figs. 5.8c and 5.8d. The index of refraction of the HOE/eq. lens is $n_c = (n_r - 1)\lambda_c/\lambda_r + 1$ and its curvatures are shown in Fig. 5.8b. Rays are traced from A to B and the spot size at B is minimized by adjusting lengths t_1 , t_2 , and t_3 (but not the length $[-z_c]!$).

Fig. 5.8. Constructing a reflecting HOE -- (a) reconstruction geometry; (b) equivalent lens ($n_r = 101$); (c) construction geometry; (d) constructing optical system; (e) computer model with HOE equivalent lens ($n_c = \sec \gamma_c / \gamma_r + 1$).

(d)

(e)

Fig. 5.8.--Continued

Conclusions

Using the techniques described here, the image quality of holographic optical elements can be greatly improved. In fact, if the quality of the emulsion and its substrate are good enough, diffraction limited optics should be obtainable.

Experimental verification in Chapters III and IV use this design technique. The examples are presented there.

CHAPTER VI

CONCLUSIONS

With the new ideas presented here, the design of systems containing HOE's has been made easier and cheaper, and better image quality can be obtained.

Using the HOE lens analog such systems are easier and cheaper to design because no special diffraction based computer code is required for the geometric design. Any lens design code will do; the big lens codes are in-expensive to use and will accept tilted and decentered elements and many strange surface shapes. Finally, lens design codes are widely used and the input and output formats are widely understood.

Better image quality can be obtained for two reasons: First, the whole system, HOE's, lenses, and mirrors, can be optimized all together rather than in parts. Second, constructing HOE's with aberrated beams allows the designer much more control over the aberrations of the HOE.

The efficiency and image quality of thin HOE's have always been optimized separately. The image quality is solely a function of the constructing conjugates. The

efficiency depends on the irradiating energy per unit area and the darkroom procedure.

The image quality can be improved in many systems (containing thin HOE's) by constructing the HOE's with spherically aberrated wavefronts. The system's optical quality is optimized with the HOE represented by an equivalent lens. The surface curvature and the aspheric coefficients of the lens analog can all be varied during the optimization. Then the HOE constructing system can be optimized with a lens design computer code by adjusting the curvatures and spacings of the lenses in the aberration generating systems (the equivalent lens is fixed during the second optimization).

Classically, thick HOE's have been constructed with spherical waves. The image quality is a function of the fringe spacing and the efficiency depends on the fringe tilt. These are coupled during the construction so one has to suffer if the other is optimized. Using the theory described here, the image quality can be optimized during the geometric design as described in the previous paragraph. Then the efficiency can be optimized by "tailoring" the two aberrated constructing beams separately so as to optimize the fringe tilt and spacing at several points in the aperture.

APPENDIX A

FIRST AND THIRD ORDER PROPERTIES OF HOLOGRAPHIC OPTICAL ELEMENTS

In this section the first and third order aberrations of a general planar holographic optical element exposed with two point sources are calculated. The point sources do not have to lie on a common normal. The third order aberrations are also calculated using thin lens theory as described by Hopkins (1950) and Welford (1974). The imaging properties calculated here check with those calculated from diffraction theory by Champagne (1967) and Meier (1965).

Also calculated in this section are the third order aberrations of a hologram constructed on a spherical substrate using two point sources on a common normal.

First Order Properties

The first-order properties of the two-lens system, including the principal planes, nodal points, focal length, and image position can be determined from thin lens theory.

The principal planes of the equivalent lens are inside of it; hence, they are coplanar with the grating. The nodal points are in the principal planes on a line connecting the two exposing points (Fig. A.1).

Fig. A.1. Location of nodal points.

The focal lengths of the two plano-convex lenses are $f_1 = z_1/\mu$ and $f_2 = z_2/\mu$ where $\mu = \lambda_r/\lambda_c$, λ_r being the reconstructing wavelength and λ_c the constructing wavelength. The power of the two lenses together is

$$\phi = \mu(1/z_1 - 1/z_2) \quad (\text{A.1})$$

Figure A.2 shows the image (x_4, y_4, z_4) of a general object point (x_3, y_3, z_3) . The image plane is perpendicular to the z axis at a distance

$$z_4 = (1/z_3 - \phi)^{-1} \quad (\text{A.2})$$

The image is located at the intersection of the image plane and a line connecting the nodal point (Fig. A.1) and the object point.

$$y_4 = y_3(z_4/z_3) \quad (\text{A.3})$$

$$x_4 = x_N + (x_3 - x_N)z_4/z_3 \quad (\text{A.4})$$

Third Order Aberrations

In this section the third-order aberrations are computed using the lens model. First, the third-order aberrations of a thin lens with a centered pupil are specialized to represent a lens with an infinite index of refraction. Then the effect of a decentered pupil is considered. With a decentered pupil, the spherical aberration and Petzval curvature are unchanged. The coma is equal to the central coma plus a contribution from the

Fig. A.2. General object and image points.

spherical. The astigmatism is altered by contributions from both the coma and spherical. The aberrations presented are valid only for object points in the xz plane. The aberrations of a general object point are discussed by Champagne (1967).

For a thin lens with a centered pupil the spherical aberration, coma, astigmatism, and Petzval curvature are found in Hopkins (1950).

$$S_I = 1/4 h^4 \phi^3 \left\{ \frac{n+2}{n(n-1)^2} X^2 + \frac{4(n+1)}{n(n-1)} XY + \frac{n^2}{(n-1)^2} + \frac{3n+2}{n} Y^2 \right\} + h^4 \alpha \quad (A.5)$$

$$S_{II} = 1/2 \bar{u} h^3 \phi^2 \left\{ \frac{n+1}{n(n-1)} X - \frac{2n+1}{n} Y \right\} \quad (A.6)$$

$$S_{III} = \bar{u}^2 h^2 \phi \quad (A.7)$$

$$S_{IV} = \bar{u}^2 h^2 \phi / n \quad (A.8)$$

h = radius of clear aperture

$X = \frac{c_1 + c_2}{c_1 - c_2}$ where c_1 and c_2 are the surface curvatures of a singlet lens

$Y = \frac{u_1 + u_2}{u_1 - u_2}$ where u_1 and u_2 are the marginal ray angles upon entry and exit from the singlet

α is a fourth-order aspheric term

$\bar{u}$ is the chief ray angle when this element is the system's stop.

If the refractive index becomes very large and the shape factor X is ± 1 , (for a plano-convex lens), then the aberration equations reduce to

$$S_I \approx 1/4 h^4 \phi^3 (1 + 3Y^2) + h^4 \alpha \quad (\text{A.9})$$

$$S_{II} \approx -\bar{u} h^3 \phi^2 Y \quad (\text{A.10})$$

$$S_{III} \approx \bar{u}^2 h^2 \phi \quad (\text{A.11})$$

$$S_{IV} \approx 0 \quad (\text{A.12})$$

The powers of the two plano-convex lenses are functions of the wavelength $\mu = \lambda_r / \lambda_c$ and the exposing points

$$\phi_1 = \mu / z_1 \quad (\text{A.13})$$

$$\phi_2 = -\mu / z_2 \quad (\text{A.14})$$

The aspheric term α can be found from the equation for the hyperbolic surface of the "lens" (Eq. (2.6)). Using Eq. (2.6) we can express the axial thickness of the lens z in terms of x and y .

$$z = 1/n_o \{ z_1 - \sqrt{x^2 + y^2 + z_1^2} \} \\ \approx -\frac{x^2 + y^2}{2n_c z_1} + \frac{(x^2 + y^2)^2}{8n_c^3 z_1^3} + \dots \quad (\text{A.15})$$

We have expanded z in a Taylor series. The first term, when multiplied by the n_r represents the power of the system. The aspheric term α is equal to the second term multiplied by n_r . (The factor $1/8$ goes away because of the

definition of S_I .) Substituting α into Eq. (A.9) produces the spherical aberration of the first lens.

$$S_I^{(1)} = 1/4 h^4/z_1^3 \{ \mu^3(1+3Y_1^2) - 4\mu \} \quad (A.16)$$

The spherical aberration of the second lens is

$$S_I^{(2)} = -1/4 h^4/z_2^3 \{ \mu^3(1+3Y_2^2) - 4\mu \} \quad (A.17)$$

The conjugate factors Y_1 and Y_2 are

$$Y_1 = 1 - (2/\mu) z_1/z_3 \quad (A.18)$$

$$Y_2 = 1 + 2z_2/z_1 - (2/\mu) z_2/z_3 \quad (A.19)$$

The spherical aberration for the holographic element is the combination of the aberration for both lenses.

$$\begin{aligned} S_I &= S_I^{(1)} + S_I^{(2)} \\ &= \mu h^4/4 \{ (\mu^2-1)(1/z_1^3 - 1/z_2^3) \\ &\quad + 3(1/z_1 - 1/z_2)(1/z_3^2 - \mu^2/z_1 z_2) \\ &\quad - 3\mu/z_3(1/z_1 - 1/z_2)^2 \} \end{aligned} \quad (A.20)$$

The coma term includes both the central coma and the spherical aberration resulting from the decentered pupil.

$$S_{II} = S_{II}^{(1)} + S_{II}^{(2)} - 4[x_1 S_I^{(1)} + x_2 S_I^{(2)}] \quad (A.21)$$

The chief ray angles are

$$\bar{u}_1 = \frac{x_1 - x_3}{z_3} \quad (A.22)$$

$$\bar{u}_2 = \frac{x_2 - x_3}{z_3} + \mu \frac{x_1 - x_2}{z_1} \quad (\text{A.23})$$

The coma for the holographic lens is

$$\begin{aligned} S_{II} = & h^3 \mu \{ 1/z_1^2 [(\mu^2 - 1)x_1/z_1 - \mu^2 x_2/z_2 - \mu x_3/z_3] \\ & + 1/z_2^2 [\mu^2 x_1/z_1 - (\mu^2 - 1)x_2/z_2 - \mu x_3/z_3] \\ & + 1/z_3^2 [x_1/z_1 - x_2/z_2] \\ & + 2[\mu x_1/z_1 - \mu x_2/z_2 - x_3/z_3] \cdot [\frac{-\mu}{z_1 z_2} + \frac{1}{z_2 z_3} - \frac{1}{z_1 z_3}] \} \quad (\text{A.24}) \end{aligned}$$

The astigmatism can be computed in the same way.

$$\begin{aligned} S_{III} = & S_{III}^{(1)} + S_{III}^{(2)} - 2x_1 S_{II}^{(1)} - 2x_2 S_{II}^{(2)} \\ & + x_1^2 S_I^{(1)} + x_2^2 S_I^{(2)} \quad (\text{A.25}) \end{aligned}$$

The astigmatism for the decentered pupil is

$$\begin{aligned} S_{III} = & h^2 \mu \{ (\frac{x_1}{z_1})^2 [(\mu^2 - 1)/z_1 - \mu^2/z_2 - \mu/z_3] \\ & + (\frac{x_2}{z_2})^2 [\mu^2/z_1 - (\mu^2 - 1)/z_2 - \mu/z_3] \\ & + (\frac{x_3}{z_3})^2 [1/z_1 - 1/z_2] \\ & + 2(\mu \frac{x_1 x_2}{z_1 z_2} + \frac{x_1 x_3}{z_1 z_3} - \frac{x_2 x_3}{z_2 z_3}) [1/z_3 - \mu/z_1 + \mu z/2] \} \quad (\text{A.26}) \end{aligned}$$

Third Order Aberrations of a HOE on a
Spherical Substrate

The third-order aberrations do not add as simply as in the plane hologram case. Third-order aberrations are dependent on the pupil height h . If the two exposing centers and the center of the substrate are not collinear, then the "h" heights are not measured in the same plane. Hence a simple addition is not possible.

Third-order aberrations can be computed if the two exposing centers are collinear with the substrate center. If they are collinear, then the hologram can be viewed as a single lens with shape factor (Hopkins, 1950):

$$X = \frac{c_1 + c_2}{c_1 - c_2} \approx 2n_c cf \quad (\text{A.27})$$

that grows as the index n_c at the exposing wavelength λ_c is increased. From Eqs. (A.5) to (A.8), the aberrations for a hologram on a spherical substrate with a centered pupil can be determined:

$$S_I = h^4 / (4f^3) \mu \{ \mu^2 [4(cf)^2 - 8cfY + 3Y^2] - [4(cf)^2 - 8cfY_O + 3Y_O^2] \} \quad (\text{A.28})$$

$$S_{II} = h^3 \bar{u} \mu^2 / f^2 \{ cf - Y \} \quad (\text{A.29})$$

$$S_{III} = h^2 \mu \bar{u}^2 / f \quad (\text{A.30})$$

$$S_{IV} = 0 \quad (\text{A.31})$$

$$S_V = 0 \quad (\text{A.32})$$

c = curvature of surface

f = focal length at exposing wavelength (λ_c)

$\bar{u}$ = principal ray angle

Y_o = (Hopkins, 1950) conjugate variable Y
describing constructing geometry

For an off-axis pupil, the coma and astigmatism are related to the on-axis aberrations by Eqs. (A.21) and (A.25).

APPENDIX B

THIRD-ORDER ABERRATIONS OF A THICK TRANSMITTING HOE

The third-order spherical aberration with which a thick transmitting HOE should be constructed is calculated here. We proceed much the same as in Chapter III. The third order spherical aberration which can be viewed as the third order variation of power as was calculated by Champagne (1967)

$$\begin{aligned} S_C - S'_C &= \lambda_C / \lambda_r (S_r - S'_r) \\ &+ h_o^4 \{ \lambda_C / \lambda_r [(z_r)^{-3} - (z'_r)^{-3}] \\ &- (z_C)^{-3} + (z'_C)^{-3} \} \end{aligned} \quad (B.1)$$

The Bragg angle's third order variation is also calculated the same as in the paraxial case. The third order approximation to the refraction Eqs. (3.2) and (3.4) are

$$B_r = 1/n_r \sin \theta_r + \frac{\sin^3 \theta_r}{6n_r} \quad (B.2)$$

$$B'_r = 1/n_r \sin \theta'_r + \frac{\sin^3 \theta'_r}{6n_r} \quad (B.3)$$

The equation for reflection off of the "Venetian Blind" is the same:

$$\alpha_r = 1/2(B_r + B'_r) \quad (B.4)$$

We now must relate θ_r and θ'_r to the distance from the HOE's centerline, y , and the wavefront tilt due to spherical aberration. Referring to Fig. 3.1, we can see that

$$\theta'_r = u'_r - \gamma'_r \quad (\text{B.5})$$

The angle γ'_r due to the spherical aberration is small and given by

$$\gamma'_r = \frac{\partial}{\partial y} (1/8 S'_r y^4 / h_o^4) = 1/2 S'_r y^3 / h_o^4 \quad (\text{B.6})$$

From Eq. (B.5)

$$\begin{aligned} \sin \theta'_r &= \sin u'_r \cos \gamma'_r - \cos u'_r \sin \gamma'_r \\ &\sim \sin u'_r - \gamma'_r \end{aligned} \quad (\text{B.7})$$

This approximation is only valid for $u'_r < 20^\circ$.

Finally, expand $\sin u'_r$ in terms of y/z'_r

$$\sin u'_r = y/z'_r - 1/2 (y/z'_r)^3 \quad (\text{B.8})$$

so

$$\sin \theta'_r = y/z'_r - 1/2 (y/z'_r)^3 + 1/2 S'_r y^3 / h_o^4 \quad (\text{B.9})$$

There will be an identical equation for the other reconstructing beam

$$\sin \theta_r = y/z_r - 1/2 (y/z_r)^3 - 1/2 S_r y^3 / h_o^4 \quad (\text{B.10})$$

Putting Eqs. (B.9) and (B.10) into Eqs. (B.2) and (B.3) and then introducing the results in Eq. (B.4) produces the third order approximation to the Bragg angle (keeping first and third order terms)

$$\alpha_r = 1/2n_r \{ [1/z_r + 1/z'_r]y - (1/2 - 1/6n_r^2) [1/(z'_r)^3 + 1/z_r^3]y^3 - 1/2(S_r + S'_r)y^3/h_o^4 \} \quad (B.11)$$

The thickness of the emulsion may change between construction and reconstruction. The third order approximation of Eq. (3.6) is given by

$$\alpha_c \sim t_r/t_c \{ \alpha_r + \frac{\alpha_r^3}{3} [1 - (t_r/t_c)^2] \} \quad (B.12)$$

The Bragg angle upon reconstruction α_c is described by an equation similar to (B.11). Putting α_c and α_r into Eq. (B.12) and keeping only first and third order terms gives

$$\begin{aligned} & 1/2n_c \{ [1/z_c + 1/z'_c]y - (1/2 - 1/6n_c^2) [1/(z'_c)^3 + 1/z_c^3] \\ & - 1/2[S_c + S'_c]y^3/h_o^4 \} = 1/(2n_r) t_r/t_c \{ [1/z_r + 1/z'_r]y \\ & - (1/2 - 1/6n_r^2) [1/(z'_r)^3 + 1/z_r^3]y^3/h_o^4 - 1/2[S_r + S'_r]y^3/h_o^4 \\ & + 1/12n_r^2 [1 - (t_r/t_c)^2] [1/z_r + 1/z'_r]^3 y^3/h_o^4 \} \quad (B.13) \end{aligned}$$

This can be separated into a part linear in x which is the same as Eq. (3.9) and a third order part

$$\begin{aligned} S_c + S'_c &= \frac{t_r n_c}{t_c n_r} (S'_r + S_r) + h_o^4 \{ \frac{t_r n_c}{t_c n_r} [(1 - \frac{1}{3n_r^2}) [(z'_r)^{-3} + (z_r)^{-3}] \\ &- \frac{1}{6n_r^2} [1 - (t_r/t_c)^2] [1/z'_r + 1/z_r]^2] \\ &- (1 - \frac{1}{3n_c^2}) [(z'_c)^{-3} + (z_c)^{-3}] \} \quad (B.14) \end{aligned}$$

Equations (B.1) and (B.14) can be solved yielding (3.12).

APPENDIX C

CONSTRUCTING A THICK REFLECTING HOE

The parameters for constructing a thick reflecting HOE are derived here. We wish to calculate the constructing conjugates (z_c and z'_c) and the combined amount of third order spherical aberration (S_c and S'_c) in the two beams. Thus we have three unknowns and need three relationships. Two equations can be found in Champagne's (1967) work, namely the power of a HOE and its third order spherical aberration.

$$1/z'_c + 1/z_c = \lambda_c/\lambda_r (1/z'_r + 1/z_r) \quad (C.1)$$

$$S_c + S'_c = \{ (z'_c)^{-3} + (z_c)^{-3} - \lambda_c/\lambda_r [(z'_r)^{-3} + (z_r)^{-3}] \} h_o^4 \\ + \lambda_c/\lambda_r (S_r + S'_r) \quad (C.2)$$

Another relationship can be generated by assuming the Bragg condition is met to third order. Referring to Fig. 4.2, the fringe angle inside the emulsion is

$$\alpha_c = 1/2 (B_c + B'_c) \quad (C.3)$$

where B_c and B'_c are the angles of the constructing rays in the emulsion. These ray angles are related to the ray angles outside the emulsion through Snell's law

$$\begin{aligned}\sin B_c &= 1/n_c \sin \theta_c \\ \sin B'_c &= 1/n_c \sin \theta'_c\end{aligned}\tag{C.4}$$

The angle θ_c is the sum of the paraxial angle u_c shown in Fig. 4.1 minus the wavefront tilt due to the spherical aberration

$$\theta_c = u_c - \gamma_c\tag{C.5}$$

where

$$\gamma_c = \frac{\partial}{\partial y}\{\gamma_c\} = 1/2 S_c y^3/h_o^4\tag{C.6}$$

With the previous three relationships we can write B_c as a function of z_c , S_c , n_c , and y . A similar expression can be written for B'_c . Both of these expressions can be substituted into Eq. (C.3) giving α_c in terms of the construction parameters.

We need a relationship between the construction fringe angle α_c and the fringe angle after the emulsion is processed α_r . Because the fringe angles are so small, it seems reasonable to assume that any shrinkage would be normal to the substrate, not along the fringe. Thus we write

$$\tan \alpha_r = t_r/t_c \tan \alpha_c\tag{C.7}$$

Combining Eqs. (C.1) and (C.5) through (C.7), and Eq. (4.1), and approximating the trigonometric functions to third order in the aperture variable y , we find,

$$\begin{aligned}
& -6[S_c + S'_c]/h_o^4 - [6 - 2(n_c)^{-2}] \cdot [(z'_c)^{-3} + (z_c)^{-3}] \\
& + (n_c)^{-2} [1/z_c + 1/z'_c]^3 = \lambda_c/\lambda_r \{ -6[S_r + S'_r]/h_o^4 \\
& - [6 - 2(n_r)^{-2}] [(z'_r)^{-3} + (z_r)^{-3}] \\
& + (n_r)^{-2} [1/z_r + 1/z'_r]^3 \} \tag{C.8}
\end{aligned}$$

Solving together Eqs. (C.1), (C.2), and (C.8) produces the construction geometry Eqs. (4.2) and (4.3).

APPENDIX D

ACHROMATIC TRIPLET USING HOLOGRAPHIC OPTICAL ELEMENTS

Introduction

Two- and three-element combinations of holographic elements producing color corrected imagery have been discussed by several authors, most notably by Katyl (1972) and Latta (1972). Recently, Bennett (1976) described the theoretical limitations of a two-element photographic system. He also calculated one condition to be met by a three-element color corrected system. In this work, we discuss the three-element holographic system in more detail.

With a correctly designed three-element system, we can set the derivatives with respect to wavelength of both the focal length and the back focal distance equal to zero at the reconstructing wavelength. Also, if either the front or rear element is chosen as the stop, the primary lateral color will be zero.

A color corrected three-element holographic system must have negative power. However, the rear element can be much smaller in diameter than the front element; if it is followed by a small converging lens, we have a lightweight, low cost imaging system with a large collecting aperture.

Development

The paraxial equations describing the marginal ray height for the system shown in Fig. D.1 are

$$y_2 = 1 - \phi_1 l_1 \quad (D.1)$$

$$u_2 = \phi_1 + y_2 \phi_2 \quad (D.2)$$

$$y_3 = y_2 - u_2 l_2 \quad (D.3)$$

$$u_3 = u_2 + y_3 \phi_3 \quad (D.4)$$

where the object is assumed to be at infinity and the ray height y is unity at the first element. The ray angles u are defined as positive down. The power of each element ϕ is a linear function of the reconstructing wavelength; thus, $\phi = \phi_o \lambda / \lambda_o$.

Fig. D.1. Achromatic triplet ($y_2 = y_3 = -1/4$, $u_3 = 1$).

The power of the system is the negative of the angle u_3 . We want a color corrected system as described by Bennett (1976), so we specify that the derivative of the power with respect to wavelength be zero:

$$\frac{\partial u_3}{\partial \lambda} = 0 \quad (D.5)$$

The back focal distance (Smith, 1966) is a linear function of the power u_3 and the marginal ray height on the last element of the system y_3 . The back focal distance will not vary with wavelength if neither u_3 nor y_3 changes with wavelength; hence, we specify

$$\frac{\partial u_3}{\partial \lambda} = 0 \quad (D.6)$$

For our color corrected system, we have two color conditions to be met [Eqs. (D.5) and (D.6)], and the system's power to be specified. However, we have five unknowns: three element powers (ϕ_1 , ϕ_2 , and ϕ_3) and two spacings (l_1 and l_2). Thus, we can specify two more unknowns: the marginal ray heights on the second and third elements. (Remember the front element has unit height.)

We can solve the set of nonlinear Eqs. (D.1)-(D.4) yielding

$$\phi_1 = u_3 \left(\frac{y_2 - y_3}{1 - y_3} - \frac{y_2}{1 - y_2} \right) \quad (D.7)$$

$$l_1 = \frac{1 - y_2}{\phi_1} \quad (D.8)$$

$$\phi_2 = \frac{u_3}{1-y_2} \quad (D.9)$$

$$l_2 = \frac{1-y_3}{u_3} \quad (D.10)$$

$$\phi_3 = u_3 \frac{1-y_3}{y_3(1-y_3)} \quad (D.11)$$

It is interesting that, if we choose either the front or the rear element as the stop, the primary lateral color is zero. Let us consider the case where the rear element is the stop. A convenient (scalable) chief ray $\bar{y}$ would have unit height on the middle element ($\bar{y}_2 = 1$) and pass through the center of the rear element ($\bar{y}_3 = 0$). The ray height on the front element would then be

$$\bar{y}_1 = 1 + l_1(1/l_2 - \phi_2) \quad (D.12)$$

Primary lateral color (PLC) is expressed as

$$PLC = \sum_{i=1}^3 \phi_i y_i \bar{y}_i \quad (D.13)$$

$$= (1 + \frac{u_3}{\phi_1} \frac{y_3 - y_2}{1 - y_3}) \phi_1 + y_2 \frac{u_3}{1 - y_2} = 0 \quad (D.14)$$

Identical algebra will show that the PLC is zero when the front element is the stop.

A system has been designed using Eqs. (D.7)-(D.11), and then Eqs. (D.5), (D.6), and D.14) were verified using first-order ray tracing.

Why must the system have negative power? The only constraints are on the element spacings l_1 and l_2 ; they must be greater than zero. A converging system requires that u_3 and y_3 be both positive or both negative. If they are both negative, then from Eq. (D.10), we can see that no negative value of y_3 produces a positive length l_2 . What if they are both positive? From Eq. (D.10) we see that $y_3 < 1$. Now combining Eqs. (D.7) and (D.8) we get

$$\frac{1}{l_1} = -u_3 \left[+ \frac{y_2^2}{(1-y_2)^2} + \frac{y_3}{1-y_3} \right] \quad (D.15)$$

The term $1/(1-y_3) > 1$, so $y_3/(1-y_3) > 0$. The squared term is also positive, so $1/l_1$ must be negative, which is not physically possible. Thus, the system must have negative power.

There are two regions of solution, both with negative power. First

$$u_3 > 0 \quad (D.16)$$

$$y_3 < 0 \quad (D.17)$$

$$\left(\frac{y_2}{1-y_2} \right)^2 < \frac{-y_3}{1-y_3} \quad (D.18)$$

The minimum total length for the system (l_1+l_2) occurs when $y_2 \rightarrow 0$ and $y_3 = -1$. This is not necessarily a practical result, but it does indicate a limiting case.

The second region of solution is described by

$$u_3 < 0 \quad (D.19)$$

$$y_3 > 1 \quad (D.20)$$

$$\left(\frac{y_2}{1-y_2}\right)^2 > \frac{-y_3}{1-y_3} \quad (D.21)$$

In this case, the rear element is larger than the front element, a solution of limited utility.

Application

A lightweight, low cost imaging system can be constructed by placing a small diameter converging lens behind a holographic triplet (Eqs. [D.16]~[D.18]) as shown in Fig. D.2. The lens will introduce some axial chromatic aberrations, but these can easily be balanced by adjusting the powers and spacings of the holographic elements. The third-order spherical aberration, spherochromatism, and coma can also be nulled out for the system by introducing the appropriate amounts of spherical aberration in each element.

Conclusions

A very simple algebraic design scheme has been presented that generates color corrected three-element holographic systems. The system was shown to have negative power and one of two configurations, as described by Eqs.

Fig. D.2. Achromatic triplet lens imaging system.

(D.16)-(D.21). One of these configurations could be used for a lightweight telescope when coupled with a converging lens.

REFERENCES

- Bausch & Lomb, "Abb 3L Reference Manual" Cat. No. 33-45-58-01; B & L, Rochester, N. Y., (n.d.).
- Bennett, S. J., Appl. Opt., 15, 542 (1976).
- Bryngdahl, Olof, Appl. Opt., 11, 195 (1972).
- Champagne, E. B., J. Opt. Soc. Am., 57, 51 (1967).
- Collier, R. J., C. B. Burchart, and L. H. Lin, Optical Holography, Academic Press, N. Y. (1971).
- Gara, A. D., and F. T. S. Yu, Appl. Opt., 10, 1324 (1971).
- Hopkins, H. H. Wave Theory of Aberrations, Clarendon Press (1950).
- Katyl, R. H., Appl. Opt., 11, 1241 (1972).
- Kogelnik, H., Bell Sys. Tech. J., 48, 2909 (1969).
- Latta, J. N., Appl. Opt., 10, 599 (1971).
- Latta, J. N., Appl. Opt., 11, 1686 (1972).
- Latta, J. N., and R. C. Fairchild, Soc. Phot. Inst. Engr. Proc., San Diego (1973).
- Leitz, Catalogue No. 500-101-13, "Interference Systems," Rockleigh, N. J. (1973).
- Longhurst, R. S., Geometrical and Physical Optics, Jarrold, Norwich, England (1967).
- McCauley, D. G., C. E. Simpson, and W. J. Murback, Appl. Opt., 12, 232 (1973).
- Meier, R. W., J. Opt. Soc. Am., 55, 987 (1965).
- Offner, Abe, Appl. Opt., 2, 153 (1963).
- Offner, Abe, J. Opt. Soc. Am., 56, 1509 (1966).

- Scientific Calculations, Inc., ACCOS V Users Guide,
Norwalk, Ct. (1970).
- Smith, W. J., Modern Optical Engineering, McGraw-Hill,
N. Y. (1966).
- Stavroudis, O. N., The Optics of Rays, Wavefronts and
Caustics, Academic Press (1972).
- Turner, A. F., Professor, Department of Optical Sciences,
University of Arizona, personal communication
(1970).
- Vilkomerson, D. H. R., and D. Bostwich, Appl. Opt., 6,
1270 (1967).
- Welford, W. T., Aberrations of the Symmetrical Optical
System, Academic Press (1974).